

Is Now Part of



ON Semiconductor®

To learn more about ON Semiconductor, please visit our website at www.onsemi.com

Please note: As part of the Fairchild Semiconductor integration, some of the Fairchild orderable part numbers will need to change in order to meet ON Semiconductor's system requirements. Since the ON Semiconductor product management systems do not have the ability to manage part nomenclature that utilizes an underscore (_), the underscore (_) in the Fairchild part numbers will be changed to a dash (-). This document may contain device numbers with an underscore (_). Please check the ON Semiconductor website to verify the updated device numbers. The most current and up-to-date ordering information can be found at www.onsemi.com. Please email any questions regarding the system integration to Fairchild guestions@onsemi.com.

ON Semiconductor and the ON Semiconductor logo are trademarks of Semiconductor Components Industries, LLC dba ON Semiconductor or its subsidiaries in the United States and/or other countries. ON Semiconductor owns the rights to a number of patents, trademarks, copyrights, trade secrets, and other intellectual property. A listing of ON Semiconductor's product/patent coverage may be accessed at www.onsemi.com/site/pdf/Patent-Marking.pdf. ON Semiconductor reserves the right to make changes without further notice to any products herein. ON Semiconductor makes no warranty, representation or guarantee regarding the suitability of its products for any particular purpose, nor does ON Semiconductor assume any liability arising out of the application or use of any product or circuit, and specifically disclaims any and all liability, including without limitation special, consequential or incidental damages. Buyer is responsible for its products and applications using ON Semiconductor products, including compliance with all laws, regulations and safety requirements or standards, regardless of any support or applications information provided by ON Semiconductor. "Typical" parameters which may be provided in ON Semiconductor data sheets and/or specifications can and do vary in different applications and actual performance may vary over time. All operating parameters, including "Typicals" must be validated for each customer application by customer's technical experts. ON Semiconductor does not convey any license under its patent rights nor the rights of others. ON Semiconductor products are not designed, intended, or authorized for use as a critical component in life support systems or any EDA Class 3 medical devices or medical devices with a same or similar classification in a foreign jurisdiction or any devices intended for implantation in the human body. Should Buyer purchase or use ON Semiconductor products for any such unintended or unauthorized application, Buyer shall indemnify and hold ON Semiconductor and its officer



August 2010

FAN5343

6-LED系列集成肖特基二极管和单线数字接口的升压 LED 驱动器

产品特性

- 异步升压变换器
 - Vour 可达 24V
- 内置肖特基二极管
- 输出功率可达500mW
- 输入电压范围: 2.7V-5.5V
- 单线数控接口,可设置LED亮度等级
 - 32级线性调整
- 固定开关频率: 1.2MHz
- 软启动
- 输入欠压锁定(UVLO)
- 输出过压保护 (OVP)
- 短路检测
- 热关闭保护() TSD
- 小型 6引脚 2.0 x 2.0 x 0.55mm U型封装MLP

适用范围

- 移动电话
- 移动互联网设备
- 便携式媒体播放器
- PDA、DSC、MP3 播放器

订购信息

器件型号	温度范围	封装	包装
FAN5343UMPX	-40 至 +85°C	6-引脚超薄模塑无铅封装(UMLP)	卷带

说明

FAN5343 为异步恒流LED驱动器,可以向6个串联的LED提供最高可达500mW的功率。优化设计更适用于小型装置,1.2MHz的固定开关频率从而允许使用较小的芯片电感和电容。

FAN5343采用单线数控接口,可通过数字脉冲对LED的亮度进行32级线性调整。

安全方面,器件整合了过压、过流、短路检测和热关断保护功能。此外,若电池电压过低将触发输入欠压闭锁保护。

FAN5343实现了超小型封装、2mm x 2mm x 0.55mm 6引脚U型封装符合环保和 RoHS的要求。

典型应用图




Figure 1. 典型应用

框图




Figure 2. 框图

引脚布局




Figure 3. UMLP6封装(顶视图)

引脚说明

引脚号	名称	说明
1	VOUT	升压输出电压。升压稳压器的输出。LED连接到该引脚。连接 Cour接地。
2	VIN	输入电压。连接电源并接地去耦合。CIN
3	EN	启用亮 度控制。采用数字脉冲驱动该引脚可编制亮度等级。
4	FB	电压反馈。升压稳压器可将该引脚的电压调至0.25V,以控制LED的串行电流。将该引脚连接GND和LED串阴极之间的电流设置电阻(R _{SET})。
5	SW	开关节点。电感L1在VIN和SW引脚之间。
6	GND	接地。直接限制于GND。

绝对最大额定值

如果应力超过绝对最大额定值,器件就会毁损。在推荐的工作条件之上,该器件可能无法正常运行或操作,且不建议让器件在这些条件下长期工作。此外,过度暴露在高于推荐的工作条件下,会影响器件的可靠性。绝对最大额定值仅是额定应力值。

符号	参数			最大值	单位
V _{IN}	VIN引脚上的电压		-0.3	6.0	V
V_{FB} , V_{EN}	FB与EN引脚电压		-0.3	V _{IN} + 0.3	V
V _{SW}	SW引脚上的电压		-0.3	25	V
V _{OUT}	VOUT引脚上的电压		-0.3	25	V
ESD	静电放电防护等级	人体模型满足 JESD22-A114	3.3		kV
ESD		充电器件模型 JESD22-C101	2	0.5	ΚV
TJ	结温		-40	+150	°C
T _{STG}	存储温度		-65	+150	°C
TL	引线焊接温度,10秒			+260	°C

推荐工作条件

推荐的操作条件表定义了真实器件的工作条件。指定推荐的工作条件,以确保设备的最佳性能达到数据表中的规格。飞兆半导体建议不要超过推荐工作条件,也不能按照绝对最大额定值进行设计。

符号	参数	工作条件	最小值	最大值	单位
V _{IN}	V _{IN} 电源电压	CV P P	2.7	5.5	V
V _{OUT}	V _{OUT} 电压 ⁽¹⁾	11000 50	6.2	24.0	V
I _{OUT}	Vout负载电流	500mW 最大输出功率	5	25	mA
T _A	环境温度	CAN	-40	+85	°C
TJ	结温	D. D.	-40	+125	°C

说明:

1. 应用必须确保最大和最小占空比在20-85%之间,方可满足指定范围。

热性能

结-环境之间热阻与具体应用和电路板布局有关。该数据由2s2p四层板测得,符合JESD51-JEDEC标准。特别注意的是,不要超过给定环境温度T_A时的结温 T_{J(max)}。

符号	参数	典型值	单位
θЈА	结-环境之间热阻	70	°C/W

电气规格

 V_{IN} = 2.7V 至 5.5V, T_A = -40°C至 +85°C,除非另有说明。典型值测量条件为 T_A = 25°C 且 V_{IN} = 3.6V。


符号	参数 工作条件		最小值	典型值	最大值	单位
电源			1		<u>'</u>	
I _{SD}	停机电源电流	EN = GND, V _{IN} = 3.6V		0.30	0.75	μΑ
\/	万 工识继阅估	Vin升	2.10	2.35	2.60	V
V_{UVLO}	欠压闭锁阈值	V _{IN} 降	1.90	2.15	2.40	V
V _{UVHYST}	欠压锁定滞环宽度			250		mV
EN:启用引	脚					
V_{IH}	输入电压高电平		1.2			V
V _{IL}	输入电压低电平				0.4	V
R_{EN}	EN下拉电阻		200	300	400	kΩ
t _{LO}	EN 低电平 调光时间	V _{IN} = 3.6V; 参见图14	0.5		300.0	μs
t _{HI}	压差延时	V _{IN} = 3.6V; 参见图14	0.5	10	6	μs
T _{SD}	EN 低电平,关断脉冲宽度	V _{IN} = 3.6V; 自 EN 的下降沿	1) (4)		ms
反馈和参考			0	110		
V_{FB}	反馈电压	$I_{LED} = 20$ mA 自 -40°C 至 +85°C, 2.7 $V \le V_{IN} \le 5.5V$	237	250	263	mV
I _{FB}	反馈输入电流	V _{FB} = 250mV		0.1	1.0	μА
电源输出		6 2		V	1	
R _{DS(ON)_Q1}	升压开关接通电阻	$V_{IN} = 3.6V, I_{SW} = 100 \text{mA}$		600		mΩ
NDS(ON)_Q1	开压开入按选电阻	$V_{IN} = 2.7V$, $I_{SW} = 100 \text{mA}$		650		1115.2
I _{SW(OFF)}	SW 节点漏电流 ⁽²⁾	$\begin{split} EN &= 0, \ V_{\text{IN}} = V_{\text{SW}} = V_{\text{OUT}} = 5.5V, \\ V_{\text{LED}} &= 0 \end{split}$		0.1	2.0	μА
I _{LIM-PK}	升压开关峰值电流限值	V _{IN} = 3.6V		750		mA
振荡器				Ä		
f _{SW}	升压稳压器开关频率		1.0	1.2	1.4	MHz
输出和保护	1	01-61				
V _{OVP}	升压输出过压保护 (OVP)	7 63	22.5	24.5		V
VOVP	OVP 滯环			1.0		· •
V_{TLSC}	V _{OUT} 短路检测阈值	V _{OUT} 降		V _{IN} – 1.4		V
V_{THSC}	V _{OUT} 短路检测阈值	Vouт 升		V _{IN} – 1.2		V
D_{MAX}	最大升压占空比(3.4)		85			%
D_{MIN}	最小升压占空比 ^(3,4)				20	%
T_{TSD}	热关闭			150		°C
T _{HYS}	热关闭滞环宽度			35		°C

说明:

- 2. SW 漏电流包括包括 两个内部开关的漏电流; SW 至 GND 与 SW 至 VOUT。
- 3. 未经产品测试;由设计保证
- 4. 应用必须确保最大和最小占空比在20-85%之间,方可满足指定范围。

典型特性

 $V_{IN}=3.6V,\,T_A=25^{\circ}C,\,I_{LED}=25mA,\,L=10\mu H,\,C_{OUT}=1.0\mu F$








Figure 4. 6 LED: 效率 vs LED 电流 vs. 输入电压









Figure 6. 5 LED: 效率 vs LED 电流 vs. 输入电压

Figure 7. V_{FB}输入电压过压和温度的变量,6 LED,L=10μH 且 C_{OUT}=1.0μF







Figure 8. 效率 vs.输入电压vs.温度

Figure 9. 过压保护 vs. 输入电压

典型特性

 $V_{IN}=3.6V,\,T_A=25^{\circ}C,\,I_{LED}=25mA,\,L=10\mu H,\,C_{OUT}=1.0\mu F$







Figure 10. 6 LED 的线性瞬态响应

Figure 11. FAN5343 的调光操作





VOUT_RIPPLE (50mV/Div)

Figure 12. 6 LED 的开关电压,电感电流的启动波形,V_{FB},以及 EN

Figure 13. 6 LED 的 V_{OUT}, 开关电压,电感电流的稳态波形

功能说明

概述

FAN5343 是一款电感电流模式升压的串联 LED 驱动器,通过保持 R_{SET} 电阻 0.25V 的电压实现LED电流的调节。LED 串的电流(I_{LED})的计算公式为:

$$I_{LED} = \frac{0.25}{R_{SET}} \tag{1}$$

电压 V_{OUT} 取决于每个LED上正向电压之和,再加上保持为 250mV的R_{SET}上的压降。

UVLO 和软启动

若 EN 低电平超过 1ms,芯片在 EN 升高时将进行一次 "冷启动" 软起动周期,前提是 V_{IN} 高于 UVLO 阈值。

数字接口

FAN5343采用单线数控接口,可通过数字脉冲对LED的亮度进行32级线性调整。采用单线解决方案,FAN5343就不再需要系统处理器持续提供信号来驱动LED。

数字调光控制

FAN5343 开始以最高亮度等级驱动LED。启动后,控制逻辑可接受编程脉冲通过施加在 EN 引脚的正端来逐步降低。图14 显示了FAN5343 的数字脉冲的调光控制。

过流和短路检测

升压模式工作期间,采用逐周期峰值电流限值~750mA,以保护 开关元件和检测元件免受损坏。

过压/开路保护

若 LED 串采用开路、FB 保持为 0V,且输出电压在没有过压保护(OVP)电路的情况下持续升高。当 Vour 超过24.5V 时,FAN5343 的 OVP电路将禁用升压稳压器,并持续到Vour降至22.5V以下方可启用。

热关闭

晶圆温度超过150°C时,发生复位并保持,直至晶圆冷却至125°C;此时允许电路开始软起动序列。



Figure 14. 数字脉冲调光控制图

应用信息

电感和输出电容的选择

Table 1. 建议使用的外部器件

LED 编号	L	器件型号	生产厂商	Min. C _{OUT}	器件型号	生产厂商
		LQH43MN100K03	Murata			
5, 6	10.0µH	NLCV32T-100K-PFR	TDK	1.00µF	UMK212BJ105KG	Taiyo Yuden
		VLF3010AT-100MR49-1	TDK			

推荐的器件和PCB布局




Figure 15. 推荐的器件布局


输入电容

在典型应用中,输入和输出电容应尽量靠近芯片,实现正常功能无需其他电容。但是,在测试环境中,若FAN5343通过较长的电缆供电,需要附加的输入电容(10μF)来保证功能稳定。这个电容应靠近电源线与 FAN5343评估板的连接处放置。


PCB推荐布局


- 电感应连接至 VIN,必要时可通过其他层。
- 反馈引脚可返回连接至IC下一层。

物理尺寸




TOP VIEW





BOTTOM VIEW



RECOMMENDED LAND PATTERN

NOTES:

- A. PACKAGE CONFORMS TO JEDEC MO-229 EXCEPT WHERE NOTED.
- B. DIMENSIONS ARE IN MILLIMETERS.
- C. DIMENSIONS AND TOLERANCES PER ASME Y14.5M, 1994.
- D. LANDPATTERN RECOMMENDATION IS BASED ON FSC DESIGN ONLY.
- E. DRAWING FILENAME: MKT-UMLP06Erev2.

Figure 16. 6-引脚超薄模塑无铅封装(U)MLP

封装图纸是作为一项服务,提供给考虑飞兆半导体产品的客户。具体参数可进行改动,且无需做出相应通知。请注意图纸上的版本和/或日期, 并联系飞兆半导体代表核实或获得最新版本。封装规格并不超出飞兆公司全球范围内的条款与条件,尤其指保修,保修涉及飞兆半导体的全部产品。

随时访问飞兆半导体在线封装网页,可以获得最新的封装图: http://www.fairchildsemi.com/packaging/。





SYSTEM STERNER

TinyBoost™

TinyBuck™

TinyCalc™

TinyLogic[®]

TINYOPTO**

TinyPower™

TinyPVM™

TinyWire™

TranSiC™

μSerDes™

TriFault Detect™

TRUECURRENT®*

TRADEMARKS

The following includes registered and unregistered trademarks and service marks, owned by Fairchild Semiconductor and/or its global subsidiaries, and is not intended to be an exhaustive list of all such trademarks.

2Cool™ AccuPower™ AX-CAP BitSiCTM Build it Now™ CorePLUS™ Core POWER** CROSSVOLT" CTL™ Current Transfer Logic™ DEUXPEED'

Dual Cool™ EcoSPARK® EfficientMax™ ESBC™

T® airchild®

Fairchild Semiconductor® FACT Quiet Series™ FACT®

FAST® Fast∨Core™ FETBench™ **FPSTM** F-PESTM FRFET® Global Power Resources GreenBridge™ Green FPS™ Green FPS™ e-Series™

Gmax™ GTO™ IntelliMAX™ ISOPLANAR™

Making Small Speakers Sound Louder and Better™

MegaBuck™ MICROCOUPLER™ MicroFET™ MicroPak™ MicroPak2™ MillerDrive™ MotionMax™

mWSaver™ OptoHiT™ OPTOLOGIC® OPTOPLANAR® PowerTrench® PowerXS™

Programmable Active Droop™

OFFT QSTM Quiet Series™ RapidConfigure™

Saving our world, 1mW////kW at a time™ SignalWise™

SmartMax[™] SMART START™

Salutions for Your Success™ SPM®

STEALTH™ SuperFET® SuperSOTM-3 SuperSOT™-6 SuperSOTM-8 SupreMOS®

UHC Ultra FRFET™ UniFET™ VCXTM VisualMax™ VoltagePlus™ SyncFET**

DISCLAIMER

FAIRCHILD SEMICONDUCTOR RESERVES THE RIGHT TO MAKE CHANGES WITHOUT FURTHER NOTICE TO ANY PRODUCTS HEREIN TO IMPROVE RELIABILITY, FUNCTION, OR DESIGN. FAIRCHILD DOES NOT ASSUME ANY LIABILITY ARISING OUT OF THE APPLICATION OR USE OF ANY PRODUCT OR CIRCUIT DESCRIBED HEREIN; NEITHER DOES IT CONVEY ANY LICENSE UNDER ITS PATENT RIGHTS, NOR THE RIGHTS OF OTHERS. THESE SPECIFICATIONS DO NOT EXPAND THE TERMS OF FAIRCHILD'S WORLDWIDE TERMS AND CONDITIONS, SPECIFICALLY THE WARRANTY THEREIN, WHICH COVERS THESE PRODUCTS.

LIFE SUPPORT POLICY

FAIRCHILD'S PRODUCTS ARE NOT AUTHORIZED FOR USE AS CRITICAL COMPONENTS IN LIFE SUPPORT DEVICES OR SYSTEMS WITHOUT THE EXPRESS WRITTEN APPROVAL OF FAIRCHILD SEMICONDUCTOR CORPORATION.

- Life support devices or systems are devices or systems which, (a) are intended for surgical implant into the body or (b) support or sustain. life, and (c) whose failure to perform when properly used in accordance with instructions for use provided in the labeling, can be reasonably expected to result in a significant injury of the user
- A critical component in any component of a life support, device, or system whose failure to perform can be reasonably expected to cause the failure of the life support device or system, or to affect its safety or effectiveness.

ANTI-COUNTERFEITING POLICY

Fairchild Semiconductor Corporation's Anti-Counterfeiting Policy. Fairchild's Anti-Counterfeiting Policy is also stated on our external website, www.fairchildsemi.com, under Sales Support.

Counterfeiting of semiconductor parts is a growing problem in the industry. All manufacturers of semiconductor products are experiencing counterfeiting of their parts. Customers who inadvertently purchase counterfeit parts experience many problems such as loss of brand reputation, substandard performance, failed applications, and increased cost of production and manufacturing delays. Fairchild is taking strong measures to protect ourselves and our customers from the proliferation of counterfeit parts. Fairchild strongly en courages customers to purchase Fairchild parts either directly from Fairchild or from Authorized Fairchild Distributors who are listed by country on our web page cited above. Products customers buy either from Fairchild directly or from Authorized Fairchild Distributors are genuine parts, have full traceability, meet Fairchild's quality standards for handling and storage and provide access to Fairchild's full range of up-to-date technical and product information. Fairchild and our Authorized Distributors will stand behind all warranties and will appropriately address any warranty issues that may arise. Fairchild will not provide any warranty coverage or other assistance for parts bought from Unauthorized Sources. Fairchild is committed to combat this global problem and encourage our customers to do their part in stopping this practice by buying direct or from authorized distributors.

PRODUCT STATUS DEFINITIONS

Definition of Terms

Datasheet Identification	Product Status	Definition		
Advance Information	Formative / In Design	Datasheet contains the design specifications for product development. Specifications may change in any manner without notice.		
Preliminary	First Production	Datasheet contains preliminary data; supplementary data will be published at a later date. Fairchild Semiconductor reserves the right to make changes at any time without notice to improve design.		
No Identification Needed	Full Production	Datasheet contains final specifications. Fairchild Semiconductor reserves the right to make changes at any time without notice to improve the design.		
Obsolete	Not In Production	Datasheet contains specifications on a product that is discontinued by Fairchild Semiconductor. The datasheet is for reference information only.		

Rev. 164

^{*} Trademarks of System General Corporation, used under license by Fairchild Semiconductor



ON Semiconductor and III) are trademarks of Semiconductor Components Industries, LLC dba ON Semiconductor or its subsidiaries in the United States and/or other countries. ON Semiconductor owns the rights to a number of patents, trademarks, copyrights, trade secrets, and other intellectual property. A listing of ON Semiconductor's product/patent coverage may be accessed at www.oisemi.com/site/pdf/Patent-Marking.pdf. ON Semiconductor reserves the right to make changes without further notice to any products herein. ON Semiconductor makes no warranty, representation or guarantee regarding the suitability of its products for any particular purpose, nor does ON Semiconductor assume any liability arising out of the application or use of any product or circuit, and specifically disclaims any and all liability, including without limitation special, consequential or incidental damages. Buyer is responsible for its products and applications using ON Semiconductor products, including compliance with all laws, regulations and safety requirements or standards, regardless of any support or applications information provided by ON Semiconductor. "Typical" parameters which may be provided in ON Semiconductor date sheets and/or specifications can and do vary in different applications and actual performance may vary over time. All operating parameters, including "Typicals" must be validated for each customer application by customer's technical experts. ON Semiconductor does not convey any license under its patent rights nor the rights of others. ON Semiconductor products are not designed, intended, or authorized for use as a critical component in life support systems or any FDA Class 3 medical devices or medical devices with a same or similar classification in a foreign jurisdiction or any devices intended for implantation in the human body. Should Buyer purchase or use ON Semiconductor products for any such unintended or unauthorized application, Buyer shall indemni

PUBLICATION ORDERING INFORMATION

LITERATURE FULFILLMENT:

Literature Distribution Center for ON Semiconductor 19521 E. 32nd Pkwy, Aurora, Colorado 80011 USA Phone: 303-675-2175 or 800-344-3860 Toll Free USA/Canada Fax: 303-675-2176 or 800-344-3867 Toll Free USA/Canada Email: orderlit@onsemi.com N. American Technical Support: 800–282–9855 Toll Free USA/Canada Europe, Middle East and Africa Technical Support:

Europe, Middle East and Africa Technical Support: Phone: 421 33 790 2910 Japan Customer Focus Center Phone: 81-3-5817-1050 ON Semiconductor Website: www.onsemi.com

Order Literature: http://www.onsemi.com/orderlit

For additional information, please contact your local Sales Representative